



Release Notes for Cisco ONS 15540 ESP for Cisco IOS Release 12.2(18)SV1

This document describes caveats for Cisco IOS Release 12.2(18)SV1 for the Cisco ONS 15540 ESP (Extended Services Platform).

Date: November 24, 2003

Text Part Number: OL-4892-02

Contents

This document includes the following information:

- [Introduction, page 1](#)
- [System Requirements, page 2](#)
- [New and Changed Information, page 7](#)
- [Caveats, page 8](#)
- [Limitations and Restrictions, page 10](#)
- [Related Documentation, page 10](#)
- [Obtaining Documentation, page 11](#)
- [Documentation Feedback, page 12](#)
- [Obtaining Technical Assistance, page 12](#)
- [Obtaining Additional Publications and Information, page 13](#)

Introduction

The Cisco ONS 15540 ESP is an optical transport platform that employs DWDM (dense wavelength division multiplexing) technology. With the Cisco ONS 15540 ESP, users can take advantage of the availability of dark fiber to build a common infrastructure that supports data, SAN (storage area



Corporate Headquarters:
Cisco Systems, Inc., 170 West Tasman Drive, San Jose, CA 95134-1706 USA

Copyright © 2003 Cisco Systems, Inc. All rights reserved.

networking), and TDM (time-division multiplexing) traffic. For more information about DWDM technology and applications, refer to the [Introduction to DWDM Technology](#) publication and the [Cisco ONS 15540 ESP Planning Guide](#).

System Requirements

This section describes the system requirements for Cisco ONS 15540 ESP and includes the following sections:

- [Memory Requirements, page 2](#)
- [Hardware Supported, page 2](#)
- [Determining the Software Version, page 6](#)
- [Upgrading the System Image, page 6](#)
- [Feature Set Table, page 6](#)

Memory Requirements

The DRAM memory configuration is 128 MB, which is the default for the Cisco ONS 15540 ESP.

Hardware Supported

[Table 1](#) lists the hardware components supported on the Cisco ONS 15540 ESP and the minimum software version required. See the [“Determining the Software Version”](#) section on page 6.

Table 1 Cisco ONS 15540 ESP Supported Hardware Modules and Minimum Software Requirements

Component	Part Number	Description	Minimum Software Version Required
Chassis	15540-CHSA		12.1(7a)EY2
Power supplies	15540-PWR-AC	120 to 240 VAC power supply	12.1(7a)EY2
	15540-CAB-AC	Custom AC-input power entry cable	12.1(7a)EY2
	15540-CAB-AC	North America	12.1(7a)EY2
	15540-CAB-ACA	Australia	12.1(7a)EY2
	15540-CAB-ACE	Europe	12.1(7a)EY2
	15540-CAB-CU	UK	12.1(7a)EY2
	15540-CAB-ACI	Italy	12.1(7a)EY2
	15540-CAB-ACR	Argentina	12.1(7a)EY2
Filler motherboards and filler modules	15540-COV-01	Mux/demux motherboard blank panel	12.1(7a)EY2
	15540-COV-02	Mux/demux module	12.1(7a)EY2
	15540-COV-03	Line card motherboard blank panel	12.1(7a)EY2
	15540-COV-04	Transponder module blank panel	12.1(7a)EY2
	15540-COV-06	Processor card cover panel	12.1(7a)EY2

Table 1 Cisco ONS 15540 ESP Supported Hardware Modules and Minimum Software Requirements (Continued)

Component	Part Number	Description	Minimum Software Version Required
Fans	15540-FTMP	Fan tray module populated with eight fans	12.1(7a)EY2
Processor cards	15540-CPU	Processor card without switch fabric	12.1(7a)EY2
Mux/demux motherboards	15540-MMMB-0100	Supports mux/demux modules with OSC	12.1(7a)EY2
	15540-MMMB-0200	Supports mux/demux modules without OSC	12.1(7a)EY2
Mux/demux modules without OSC	15540-MDXA-04A0	4-channel Band A	12.1(7a)EY2
	15540-MDXA-04B0	4-channel Band B	12.1(7a)EY2
	15540-MDXA-04C0	4-channel Band C	12.1(7a)EY2
	15540-MDXA-04D0	4-channel Band D	12.1(7a)EY2
	15540-MDXA-04E0	4-channel Band E	12.1(7a)EY2
	15540-MDXA-04F0	4-channel Band F	12.1(7a)EY2
	15540-MDXA-04G0	4-channel Band G	12.1(7a)EY2
	15540-MDXA-04H0	4-channel Band H	12.1(7a)EY2
	15540-MDXA-08A0	8-channel Band AB	12.1(7a)EY2
	15540-MDXA-08B0	8-channel Band CD	12.1(7a)EY2
	15540-MDXA-08C0	8-channel Band EF	12.1(7a)EY2
	15540-MDXA-08D0	8-channel Band GH	12.1(7a)EY2
15540-MDXA-16EH	16-channel Band EH	12.1(7a)EY2	
Mux/demux modules with OSC	15540-MDXA-04A0	4-channel Band A	12.1(7a)EY2
	15540-MDXB-04B0	4-channel Band B	12.1(7a)EY2
	15540-MDXB-04C0	4-channel Band C	12.1(7a)EY2
	15540-MDXB-04D0	4-channel Band D	12.1(7a)EY2
	15540-MDXB-04E0	4-channel Band E	12.1(7a)EY2
	15540-MDXB-04F0	4-channel Band F	12.1(7a)EY2
	15540-MDXB-04G0	4-channel Band G	12.1(7a)EY2
	15540-MDXB-04H0	4-channel Band H	12.1(7a)EY2
	15540-MDXB-08A0	8-channel Band AB	12.1(7a)EY2
	15540-MDXB-08B0	8-channel Band CD	12.1(7a)EY2
	15540-MDXB-08C0	8-channel Band EF	12.1(7a)EY2
	15540-MDXB-08D0	8-channel Band GH	12.1(7a)EY2
15540-MDXB-16AD	16-channel Band AD	12.1(7a)EY2	
Line card motherboards	15540-LCMB-0100	Supports four transponders with protection	12.1(7a)EY2
	15540-LCMB-0200	Supports four transponders -East	12.1(7a)EY2
	15540-LCMB-0201	Supports four transponders -West	12.1(7a)EY2

Table 1 Cisco ONS 15540 ESP Supported Hardware Modules and Minimum Software Requirements (Continued)

Component	Part Number	Description	Minimum Software Version Required
MM transponder modules	15540-TSP1-01A3	Ch 1-2 —1310-nm MM 16 to 622 Mbps with SC	12.1(7a)EY2
	15540-TSP1-03A3	Ch 3-4 — 1310-nm MM 16 to 622 Mbps with SC	12.1(7a)EY2
	15540-TSP1-05A3	Ch 5-6 —1310-nm MM 16 to 622 Mbps with SC	12.1(7a)EY2
	15540-TSP1-07A3	Ch 7-8 — 1310-nm MM 16 to 622 Mbps with SC	12.1(7a)EY2
	15540-TSP1-09A3	Ch 9-10 — 1310-nm MM 16 to 622 Mbps with SC	12.1(7a)EY2
	15540-TSP1-11A3	Ch 11-12 — 1310-nm MM 16 to 622 Mbps with SC	12.1(7a)EY2
	15540-TSP1-13A3	Ch 13-14 — 1310-nm MM 16 to 622 Mbps with SC	12.1(7a)EY2
	15540-TSP1-15A3	Ch 15-16 — 1310-nm MM 16 to 622 Mbps with SC	12.1(7a)EY2
	15540-TSP1-17A3	Ch 17-18 — 1310-nm MM 16 to 622 Mbps with SC	12.1(7a)EY2
	15540-TSP1-19A3	Ch 19-20 — 1310nm MM 16 to 622 Mbps with SC	12.1(7a)EY2
	15540-TSP1-21A3	Ch 21-22 — 1310-nm MM 16 to 622 Mbps with SC	12.1(7a)EY2
	15540-TSP1-23A3	Ch 23- 24—1310-nm MM 16 to 622 Mbps with SC	12.1(7a)EY2
	15540-TSP1-25A3	Ch 25-26—1310-nm MM 16 to 622 Mbps with SC	12.1(7a)EY2
	15540-TSP1-27A3	Ch 27-28—1310-nm MM 16 to 622 Mbps with SC	12.1(7a)EY2
	15540-TSP1-29A3	Ch 29-30—1310-nm MM 16 to 622 Mbps with SC	12.1(7a)EY2
15540-TSP1-31A3	Ch 31-32—1310-nm MM 16 to 622 Mbps with SC	12.1(7a)EY2	
SM transponder modules	15540-TSP1-01B3	Ch 1-2—1310-nm SM 16 Mbps to 2.5 Gbps with SC	12.1(7a)EY2
	15540-TSP1-03B3	Ch 3-4—1310-nm SM 16 Mbps to 2.5 Gbps with SC	12.1(7a)EY2
	15540-TSP1-05B3	Ch 5-6—1310-nm SM 16 Mbps to 2.5 Gbps with SC	12.1(7a)EY2
	15540-TSP1-07B3	Ch 7-8—1310-nm SM 16 Mbps to 2.5 Gbps with SC	12.1(7a)EY2
	15540-TSP1-09B3	Ch 9-10—1310-nm SM 16 Mbps to 2.5 Gbps with SC	12.1(7a)EY2
	15540-TSP1-11B3	Ch 11-12—1310-nm SM 16 Mbps to 2.5 Gbps with SC	12.1(7a)EY2
	15540-TSP1-13B3	Ch 13-14— 1310-nm SM 16 Mbps to 2.5 Gbps with SC	12.1(7a)EY2
	15540-TSP1-15B3	Ch 15-16—1310-nm SM 16 Mbps to 2.5 Gbps with SC	12.1(7a)EY2
	15540-TSP1-17B3	Ch 17-18—1310-nm SM 16 Mbps to 2.5 Gbps with SC	12.1(7a)EY2
	15540-TSP1-19B3	Ch 19-20—1310nm SM 16 Mbps to 2.5 Gbps with SC	12.1(7a)EY2
	15540-TSP1-21B3	Ch 21-22—1310-nm SM 16 Mbps to 2.5 Gbps with SC	12.1(7a)EY2
	15540-TSP1-23B3	Ch 23- 24—1310-nm SM 16 Mbps to 2.5 Gbps with SC	12.1(7a)EY2
	15540-TSP1-23B3	Ch 23- 24—1310-nm SM 16 Mbps to 2.5 Gbps with SC	12.1(7a)EY2
	15540-TSP1-25B3	Ch 25-26—1310-nm SM 16 Mbps to 2.5 Gbps with SC	12.1(7a)EY2
	15540-TSP1-27B3	Ch 27-28—1310-nm SM 16 Mbps to 2.5 Gbps with SC	12.1(7a)EY2
15540-TSP1-29B3	Ch 29-30 —1310-nm SM 16 Mbps to 2.5 Gbps with SC	12.1(7a)EY2	
15540-TSP1-31B3	Ch 31-32—1310-nm SM 16 Mbps to 2.5 Gbps with SC	12.1(7a)EY2	

Table 1 Cisco ONS 15540 ESP Supported Hardware Modules and Minimum Software Requirements (Continued)

Component	Part Number	Description	Minimum Software Version Required
Type 2 extended range transponder module	15540-TSP2-0100	Ch 1-2	12.1(11b)E
	15540-TSP2-0300	Ch 3-4	12.1(11b)E
	15540-TSP2-0500	Ch 5-6	12.1(11b)E
	15540-TSP2-0700	Ch 7-8	12.1(11b)E
	15540-TSP2-0900	Ch 9-10	12.1(11b)E
	15540-TSP2-1100	Ch 11-12	12.1(11b)E
	15540-TSP2-1300	Ch 13-14	12.1(11b)E
	15540-TSP2-1500	Ch 15-16	12.1(11b)E
	15540-TSP2-1700	Ch 17-18	12.1(11b)E
	15540-TSP2-1900	Ch 19-20	12.1(11b)E
	15540-TSP2-2100	Ch 21-22	12.1(11b)E
	15540-TSP2-2300	Ch 23-24	12.1(11b)E
	15540-TSP2-2500	Ch 25-26	12.1(11b)E
	15540-TSP2-2700	Ch 27-28	12.1(11b)E
	15540-TSP2-2900	Ch 29-30	12.1(11b)E
15540-TSP2-3100	Ch 31-32	12.1(11b)E	
Fixed rate SFP optics for Type 2 extended range transponder modules	15500-XVRA-01A2	ESCON and OC-3 1310-nm MM MT-RJ	12.1(11b)E
	15500-XVRA-03B1	Gigabit Ethernet and Fibre Channel (1 Gbps) 1310-nm SM MTLC	12.1(11b)E
	15500-XVRA-03B2	1-Gbps Fibre Channel and 2 Gbps Fibre Channel 1310-nm SM MTLC	12.1(11b)E
	15500-XVRA-02C1	Gigabit Ethernet and Fibre Channel (1 Gbps) 850-nm MM MTLC	12.1(11b)E
	15500-XVRA-02C2	Fibre Channel (1 Gbps and 2 Gbps) 850-nm SM MTLC	12.1(11b)E
	15500-XVRA-06B1	SONET OC-12 1310-nm SM MTLC	12.1(11b)E
	15500-XVRA-07B1	SONET OC-48 1310-nm SM MTLC	12.1(11b)E
Variable rate SFP optics	15500-XVRA-10A1	Low band (16 to 200 Mbps) variable rate, MM (1310 nm) with LC	12.1(12c)EV3
	15500-XVRA-10B1	Low band (16 to 200 Mbps) variable rate, SM (1310 nm) with LC	12.1(12c)EV3
	15500-XVRA-11A1	Mid band (200 to 622 Mbps) variable rate, MM (1310 nm) with LC	12.1(12c)EV3
	15500-XVRA-11B1	Mid band (200 to 1250 Mbps) variable rate, SM (1310 nm) with LC	12.1(12c)EV3
	15500-XVRA-12B1	High band (1.062 Gbps to 2.5 Gbps) variable rate, SM (1310 nm) with LC	12.1(12c)EV3

Determining the Software Version



Note

We strongly recommend that you use the latest available software release for all Cisco ONS 15540 ESP hardware.

To determine the version of Cisco IOS software currently running on a Cisco ONS 15540 ESP system, log in to the system and enter the **show version EXEC** command. The following sample output is from the **show version** command. The software version number is shown on the second line of the sample output.

```
Switch# show version
Cisco Internetwork Operating System Software
IOS (tm) ONS-15540 Software (ONS15540-I-M), Version 12.2(18)SV1
<Information deleted>
```

Upgrading the System Image

To ensure proper system functioning, follow the system image upgrading procedure described in the *Cisco ONS 15540 ESP Configuration Guide and Command Reference*.



Note

Always set the configuration register to 0x2102 when upgrading the system image using the **config-reg 0x2102** command in configuration mode.



Caution

Improper system image upgrades can affect system functioning and redundancy. Always follow the recommended upgrade procedures.

Feature Set Table

The Cisco IOS Release software is packaged in feature sets (also called software images) depending on the platform. Each feature set contains a specific set of Cisco IOS features. [Table 2](#) lists the Cisco IOS software feature sets available for the Cisco ONS 15540 ESP.

Table 2 *Feature Sets Supported by the Cisco ONS 15540 ESP*

Feature Set	Introduced in This Release
Gigabit Ethernet	12.1(7a)EY2
Fast Ethernet	12.1(7a)EY2
Ethernet	12.1(7a)EY2
ATM OC-3/STM-1, OC-12/STM-4, and OC-48/STM-16	12.1(7a)EY2
SONET ¹ /SDH ²	12.1(7a)EY2
POS ³	12.1(7a)EY2

Table 2 Feature Sets Supported by the Cisco ONS 15540 ESP (Continued)

Feature Set	Introduced in This Release
Coupling link	12.1(7a)EY2
Fibre Channel (1 Gbps)	12.1(7a)EY2
Fibre Channel (2 Gbps)	12.1(7a)EY2
FDDI ⁴	12.1(7a)EY2
ESCON ⁵ SM (200 Mbps)	12.1(7a)EY2
FICON ⁶ (800 Mbps)	12.1(7a)EY2
FICON (1 Gbps)	12.1(12c)EV3
Token Ring	12.1(7a)EY2
SNMP	12.1(7a)EY2
CiscoView	12.1(7a)EY2
Cisco Transport Manager	12.1(7a)EY2
IP packets	12.1(7a)EY2
OSCP ⁷	12.1(7a)EY2
APS ⁸ protocol packets	12.1(7a)EY2
Point-to-point	12.1(7a)EY2
Hubbed ring	12.1(7a)EY2
Meshed ring	12.1(7a)EY2
IBM GDPS ⁹ ETR/CLO ¹⁰	12.1(7a)EY2
IBM GDPS ⁹ coupling link	12.1(7a)EY2
2-Gbps Fibre Channel protocol monitoring on transparent transponder	12.2(18)SV
2-Gbps FICON protocol monitoring	12.2(18)SV
Functional image version diagnostics	12.2(18)SV

1. SONET = Synchronous Optical Networking
2. SDH = Synchronous Digital Hierarchy
3. POS = Packet over SONET
4. FDDI = Fiber Distributed Data Interface
5. ESCON = Enterprise Systems Connection
6. FICON = Fiber Connection
7. OSCP = Optical Supervisory Channel Protocol
8. APS = Automatic Protection Switching
9. GDPS = Geographically Dispersed Parallel Sysplex
10. ETR/CLO = external timer reference/control link oscillator

New and Changed Information

This section lists new features that appear in this and previous releases of Cisco IOS Release 12.2. The new features are sorted by release number.

New Features in Release 12.2(18)SV1

No new features are available for this release.

New Features in Release 12.2(18)SV

The following new software features are available for the Cisco ONS 15540 ESP in Cisco IOS Release 12.2(18)SV:

- 2-Gbps Fibre Channel protocol monitoring



Note 2-Gbps Fibre Channel protocol monitoring requires transponder functional image release 1.A3.

- 2-Gbps FICON protocol monitoring
- Data file with upgrade information for the ROMMON and functional images
- **show upgrade-info functional-image** command

Caveats

This section describes open and resolved severity 1 and 2 caveats and certain severity 3 caveats. The “Open Caveats” section lists open caveats that apply to the current release and may apply to previous releases. The “Resolved Caveats” sections list caveats resolved in a particular release, but open in previous releases.

Open Caveats in Release 12.2(18)SV1

- CSCec31146
Symptom: When monitoring is disabled, Loss of Light on the local transparent interface results in Loss of Sync on the far side wave interface.
Workaround: Enable monitoring on the transparent interface.

Resolved Caveats in Release 12.2(18)SV1

- CSCec28182
Symptom: Tracebacks related to CPU hog issues are seen when reprogramming the 2.5-Gbps transponder module functional image.
Workaround: None.
- CSCec59409
Symptom: Issuing a Ctrl-U when connected to a raw TL1 port causes the system to crash.
Workaround: If a TL1 port is unused, apply an IP ACL to the management Ethernet interface that blocks the incoming TCP connections to that port.

Resolved Caveats for Release 12.2(18)SV

- CSCdu53656

A Cisco device running IOS and enabled for the Border Gateway Protocol (BGP) is vulnerable to a Denial of Service (DOS) attack from a malformed BGP packet. The BGP protocol is not enabled by default, and must be configured in order to accept traffic from an explicitly defined peer. Unless the malicious traffic appears to be sourced from a configured, trusted peer, it would be difficult to inject a malformed packet. BGP MD5 is a valid workaround for this problem.

Cisco has made free software available to address this problem. For more details, please refer to this advisory, available at <http://www.cisco.com/warp/public/707/cisco-sa-20040616-bgp.shtml>.
- CSCea28131

A Cisco device running IOS and enabled for the Border Gateway Protocol (BGP) is vulnerable to a Denial of Service (DOS) attack from a malformed BGP packet. The BGP protocol is not enabled by default, and must be configured in order to accept traffic from an explicitly defined peer. Unless the malicious traffic appears to be sourced from a configured, trusted peer, it would be difficult to inject a malformed packet. BGP MD5 is a valid workaround for this problem.

Cisco has made free software available to address this problem. For more details, please refer to this advisory, available at <http://www.cisco.com/warp/public/707/cisco-sa-20040616-bgp.shtml>.
- CSCeb61427

Symptom: The system crashes when the user exits from the console after the active processor card has been removed and inserted online and is switched back to being the active processor card.

Workaround: None.
- CSCeb72528

Symptom: Client Tx fault alarm is asserted when an SFP optics is inserted or upon a y-cable switchover.

Workaround: Upgrade to Cisco IOS Release 12.1(12c)EV3 and transponder functional image version 1.A2 or higher.
- CSCec05746

Symptom: In a point-to-point network topology setup where bidirectional PSM trunk fiber protection APS is configured, and the CDL (Converged Data Link) is configured for dcc and the controller type of the mux/demux module is 0x1104 (4-channel mux/demux module without OSC), APS is unable to track a valid ethernetDcc interface. Therefore the group cannot be associated.

Workaround: Do not configure CDL as dcc for PSM APS if the corresponding mux/demux module does not have OSC ports (controller type 0x1104).
- CSCec22377

Symptom: Continuous optical performance monitoring alarms cause memory leaks that lead to bus error exceptions and an unexpected reload.

Workaround: None.
- CSCec31503

Symptom: Unable to disable APS group through SNMP. The console or Telnet session hangs indefinitely after configuration mode is entered using the SNMP **set** command.

Workaround: Do not disable the APS group through SNMP.
- CSCec31512

Symptom: When you enter the **send break** command on the active CPU and keep the active CPU in the ROM monitor (ROMmon) mode for a long time, the standby CPU may reload because of a bus error exception.

Workaround: None.

Limitations and Restrictions

This section provides limitations and restrictions for Cisco ONS 15540 ESP hardware and software.

Transponder Modules

This section contains limitations and restrictions that apply to transponder modules.

- When you insert the standby transponder module in a y-cable protected configuration, remove the cable from the transponder module before inserting the transponder module into the shelf. Failure to remove the cable might result in errors that can affect the performance of the active signal received by the client equipment.
- CRC errors may occur with 2-Gbps Fibre Channel on single-mode transponders when high input power levels are received from the client laser sources.

Data errors or link-down conditions for 2-Gbps Fibre Channel might occur when used with certain client laser sources. Transmitters in some client GBIC and SFP transceiver units might send large overshoots in optical power with signal bit transitions, causing momentary overload conditions on the transponder client side receiver. The average transmitted power level from the GBIC does not violate the overload specification of the transponder client side receiver, so a power meter does not detect the overload.

The workaround is to attenuate the signal from the client equipment to a recommended level of -12 dBm when transmitting 2-Gbps Fibre Channel services.

- Error-free transmission of some D1 video signals (defined by the SMPTE 259M standard) and test patterns (such as Matrix SDI) cannot be guaranteed by the Cisco 15500 Series because of the pathological pattern in D1 video. This well-known limitation is usually overcome by the D1 video equipment vendor, who uses a proprietary, second level of scrambling. No standards exist at this time for the second level of scrambling.

Related Documentation

Refer to the following documents for more information about the Cisco ONS 15540 ESP:

- [Regulatory Compliance and Safety Information for the Cisco ONS 15500 Series](#)
- [Cisco ONS 15540 ESP Planning Guide](#)
- [Cisco ONS 15540 ESP Hardware Installation Guide](#)
- [Cisco ONS 15540 ESP and Cisco ONS 15540 ESPx Optical Transport Turn-Up and Test Guide](#)
- [Cisco ONS 15540 ESP Configuration Guide and Command Reference](#)
- [Quick Reference for the Cisco ONS 15540 ESP and Cisco ONS 15540 ESPx CLI Commands](#)
- [Cisco ONS 15540 ESP System Alarms and Error Messages](#)
- [Cisco ONS 15540 ESP Troubleshooting Guide](#)

- *Network Management for the Cisco ONS 15540 ESP*
- *Cisco ONS 15540 ESP MIB Quick Reference*

Obtaining Documentation

Cisco provides several ways to obtain documentation, technical assistance, and other technical resources. These sections explain how to obtain technical information from Cisco Systems.

Cisco.com

You can access the most current Cisco documentation on the World Wide Web at this URL:

<http://www.cisco.com/univercd/home/home.htm>

You can access the Cisco website at this URL:

<http://www.cisco.com>

International Cisco websites can be accessed from this URL:

http://www.cisco.com/public/countries_languages.shtml

Documentation CD-ROM

Cisco documentation and additional literature are available in a Cisco Documentation CD-ROM package, which may have shipped with your product. The Documentation CD-ROM is updated regularly and may be more current than printed documentation. The CD-ROM package is available as a single unit or through an annual or quarterly subscription.

Registered Cisco.com users can order a single Documentation CD-ROM (product number DOC-CONDOCCD=) through the Cisco Ordering tool:

http://www.cisco.com/en/US/partner/ordering/ordering_place_order_ordering_tool_launch.html

All users can order annual or quarterly subscriptions through the online Subscription Store:

<http://www.cisco.com/go/subscription>

Click Subscriptions & Promotional Materials in the left navigation bar.

Ordering Documentation

You can find instructions for ordering documentation at this URL:

http://www.cisco.com/univercd/cc/td/doc/es_inpk/pdi.htm

You can order Cisco documentation in these ways:

- Registered Cisco.com users (Cisco direct customers) can order Cisco product documentation from the Networking Products MarketPlace:

<http://www.cisco.com/en/US/partner/ordering/index.shtml>

- Nonregistered Cisco.com users can order documentation through a local account representative by calling Cisco Systems Corporate Headquarters (California, USA) at 408 526-7208 or, elsewhere in North America, by calling 800 553-NETS (6387).

Documentation Feedback

You can submit e-mail comments about technical documentation to bug-doc@cisco.com.

You can submit comments by using the response card (if present) behind the front cover of your document or by writing to the following address:

Cisco Systems
Attn: Customer Document Ordering
170 West Tasman Drive
San Jose, CA 95134-9883

We appreciate your comments.

Obtaining Technical Assistance

For all customers, partners, resellers, and distributors who hold valid Cisco service contracts, the Cisco Technical Assistance Center (TAC) provides 24-hour-a-day, award-winning technical support services, online and over the phone. Cisco.com features the Cisco TAC website as an online starting point for technical assistance. If you do not hold a valid Cisco service contract, please contact your reseller.

Cisco TAC Website

The Cisco TAC website (<http://www.cisco.com/tac>) provides online documents and tools for troubleshooting and resolving technical issues with Cisco products and technologies. The Cisco TAC website is available 24 hours a day, 365 days a year.

Accessing all the tools on the Cisco TAC website requires a Cisco.com user ID and password. If you have a valid service contract but do not have a login ID or password, register at this URL:

<http://tools.cisco.com/RPF/register/register.do>

Opening a TAC Case

Using the online TAC Case Open Tool (<http://www.cisco.com/tac/caseopen>) is the fastest way to open P3 and P4 cases. (P3 and P4 cases are those in which your network is minimally impaired or for which you require product information.) After you describe your situation, the TAC Case Open Tool automatically recommends resources for an immediate solution. If your issue is not resolved using the recommended resources, your case will be assigned to a Cisco TAC engineer.

For P1 or P2 cases (P1 and P2 cases are those in which your production network is down or severely degraded) or if you do not have Internet access, contact Cisco TAC by telephone. Cisco TAC engineers are assigned immediately to P1 and P2 cases to help keep your business operations running smoothly.

To open a case by telephone, use one of the following numbers:

Asia-Pacific: +61 2 8446 7411 (Australia: 1 800 805 227)

EMEA: +32 2 704 55 55

USA: 1 800 553-2447

For a complete listing of Cisco TAC contacts, go to this URL:

<http://www.cisco.com/warp/public/687/Directory/DirTAC.shtml>

TAC Case Priority Definitions

To ensure that all cases are reported in a standard format, Cisco has established case priority definitions.

Priority 1 (P1)—Your network is “down” or there is a critical impact to your business operations. You and Cisco will commit all necessary resources around the clock to resolve the situation.

Priority 2 (P2)—Operation of an existing network is severely degraded, or significant aspects of your business operation are negatively affected by inadequate performance of Cisco products. You and Cisco will commit full-time resources during normal business hours to resolve the situation.

Priority 3 (P3)—Operational performance of your network is impaired, but most business operations remain functional. You and Cisco will commit resources during normal business hours to restore service to satisfactory levels.

Priority 4 (P4)—You require information or assistance with Cisco product capabilities, installation, or configuration. There is little or no effect on your business operations.

Obtaining Additional Publications and Information

Information about Cisco products, technologies, and network solutions is available from various online and printed sources.

- The Cisco Product Catalog describes the networking products offered by Cisco Systems, as well as ordering and customer support services. Access the Cisco Product Catalog at this URL:
http://www.cisco.com/en/US/products/products_catalog_links_launch.html
- Cisco Press publishes a wide range of general networking, training and certification titles. Both new and experienced users will benefit from these publications. For current Cisco Press titles and other information, go to Cisco Press online at this URL:
<http://www.ciscopress.com>
- Packet magazine is the Cisco quarterly publication that provides the latest networking trends, technology breakthroughs, and Cisco products and solutions to help industry professionals get the most from their networking investment. Included are networking deployment and troubleshooting tips, configuration examples, customer case studies, tutorials and training, certification information, and links to numerous in-depth online resources. You can access Packet magazine at this URL:
<http://www.cisco.com/packet>
- iQ Magazine is the Cisco bimonthly publication that delivers the latest information about Internet business strategies for executives. You can access iQ Magazine at this URL:
<http://www.cisco.com/go/iqmagazine>
- Internet Protocol Journal is a quarterly journal published by Cisco Systems for engineering professionals involved in designing, developing, and operating public and private internets and intranets. You can access the Internet Protocol Journal at this URL:
http://www.cisco.com/en/US/about/ac123/ac147/about_cisco_the_internet_protocol_journal.html
- Training—Cisco offers world-class networking training. Current offerings in network training are listed at this URL:
<http://www.cisco.com/en/US/learning/index.html>

This document is to be used in conjunction with the documents listed in the “[Related Documentation](#)” section.

CCIP, CCSP, the Cisco Arrow logo, the Cisco *Powered* Network mark, Cisco Unity, Follow Me Browsing, FormShare, and StackWise are trademarks of Cisco Systems, Inc.; Changing the Way We Work, Live, Play, and Learn, and iQuick Study are service marks of Cisco Systems, Inc.; and Aironet, ASIST, BPX, Catalyst, CCDA, CCDP, CCIE, CCNA, CCNP, Cisco, the Cisco Certified Internetwork Expert logo, Cisco IOS, the Cisco IOS logo, Cisco Press, Cisco Systems, Cisco Systems Capital, the Cisco Systems logo, Empowering the Internet Generation, Enterprise/Solver, EtherChannel, EtherSwitch, Fast Step, GigaStack, Internet Quotient, IOS, IP/TV, iQ Expertise, the iQ logo, iQ Net Readiness Scorecard, LightStream, MGX, MICA, the Networkers logo, Networking Academy, Network Registrar, *Packet*, PIX, Post-Routing, Pre-Routing, RateMUX, Registrar, ScriptShare, SlideCast, SMARTnet, StrataView Plus, Stratm, SwitchProbe, TeleRouter, The Fastest Way to Increase Your Internet Quotient, TransPath, and VCO are registered trademarks of Cisco Systems, Inc. and/or its affiliates in the U.S. and certain other countries.

All other trademarks mentioned in this document or Web site are the property of their respective owners. The use of the word partner does not imply a partnership relationship between Cisco and any other company. (0304R)

Copyright © 2003 Cisco Systems, Inc. All rights reserved.