



Release Notes for Cisco ONS 15540 ESPx for Cisco IOS Release 12.2(18)SV

This document describes caveats for Cisco IOS Release 12.2(18)SV for the Cisco ONS 15540 ESPx.

Date: June 18, 2004

Text Part Number: OL-4893-01

Contents

This document includes the following information:

- [Introduction, page 1](#)
- [System Requirements, page 2](#)
- [New Features in Release 12.2\(18\)SV, page 11](#)
- [Caveats, page 11](#)
- [Limitations and Restrictions, page 13](#)
- [Related Documentation, page 14](#)
- [Obtaining Documentation, page 14](#)
- [Documentation Feedback, page 15](#)
- [Obtaining Technical Assistance, page 16](#)
- [Obtaining Additional Publications and Information, page 17](#)

Introduction

The Cisco ONS 15540 ESPx is an optical transport platform that employs DWDM (dense wavelength division multiplexing) technology. With the Cisco ONS 15540 ESPx, users can take advantage of the availability of dark fiber to build a common infrastructure that supports data, SAN (storage area networking), and TDM (time-division multiplexing) traffic. The system uses an enhanced chassis with front fiber optic



Corporate Headquarters:
Cisco Systems, Inc., 170 West Tasman Drive, San Jose, CA 95134-1706 USA

Copyright © 2003 Cisco Systems, Inc. All rights reserved.

cable access for optical interconnections between transponder modules and optical mux/demux modules. For more information about DWDM technology and applications, refer to the [Introduction to DWDM Technology](#) publication and the [Cisco ONS 15540 ESPx Planning Guide](#).

System Requirements

This section describes the system requirements for Cisco IOS Release 12.2(18)SV and includes the following sections:

- [Memory Requirements, page 2](#)
- [Hardware Supported, page 2](#)
- [Determining the Software Version, page 9](#)
- [Upgrading the System Image, page 9](#)
- [Feature Set Table, page 10](#)

Memory Requirements

The DRAM memory configuration is 128 MB, which is the default for the Cisco ONS 15540 ESPx.

Hardware Supported

[Table 1](#) lists the hardware components supported on the Cisco ONS 15540 ESPx and the minimum software version required. See the [“Determining the Software Version”](#) section on page 9.

Table 1 Cisco ONS 15540 ESPx Supported Hardware Modules and Minimum Software Requirements

Component	Part Number	Description	Minimum Software Version Required
Chassis	15540-CHSB=	Chassis external connection system —19” RM, 14 U, 12 slots	12.1(10)EV1
Power supplies and spare power supply cables	15540-PWR-AC	120 to 240 VAC power supply	12.1(10)EV1
	15540-CAB-AC	Custom AC-input power entry cable	12.1(10)EV1
	15500-CAB-AC	North America	12.1(10)EV1
	15500-CAB-ACA	Australia	12.1(10)EV1
	15500-CAB-ACE	Europe	12.1(10)EV1
	15500-CAB-CU	UK	12.1(10)EV1
	15500-CAB-ACI	Italy	12.1(10)EV1
Blank motherboards and blank modules	15540-COV-07	Mux/demux motherboard blank panel	12.1(10)EV1
	15540-COV-08	4 / 8 Ch. mux/demux blank panel	12.1(10)EV1
	15540-COV-09	Line card motherboard blank panel	12.1(10)EV1
	15540-COV-10	Transponder module blank panel	12.1(10)EV1

Table 1 Cisco ONS 15540 ESPx Supported Hardware Modules and Minimum Software Requirements (Continued)

Component	Part Number	Description	Minimum Software Version Required
Fans	15540-FTMP=	Fan tray module populated with eight fans	12.1(10)EV1
Processor cards	15540-CPU	Processor card	12.1(10)EV1
Flash PC Cards	15500-PCMCIA16=	PCMCIA memory card 16 MB	12.1(10)EV1
	15500-PCMCIA20=	PCMCIA memory card 20 MB	12.1(10)EV1
Mux/demux motherboards	15540-MMMB-1100	Supports mux/demux modules with OSC	12.1(10)EV1
	15540-MMMB-1200	Supports mux/demux modules without OSC	12.1(10)EV1
Mux/demux modules without OSC	15540-MDXC-04A0	4-channel Band A	12.1(10)EV1
	15540-MDXC-04B0	4-channel Band B	12.1(10)EV1
	15540-MDXC-04C0	4-channel Band C	12.1(10)EV1
	15540-MDXC-04D0	4-channel Band D	12.1(10)EV1
	15540-MDXC-04E0	4-channel Band E	12.1(10)EV1
	15540-MDXC-04F0	4-channel Band F	12.1(10)EV1
	15540-MDXC-04G0	4-channel Band G	12.1(10)EV1
	15540-MDXC-04H0	4-channel Band H	12.1(10)EV1
	15540-MDXC-08A0	8-channel Band AB	12.1(10)EV1
	15540-MDXC-08B0	8-channel Band CD	12.1(10)EV1
	15540-MDXC-08C0	8-channel Band EF	12.1(10)EV1
	15540-MDXC-08D0	8-channel Band GH	12.1(10)EV1
Mux/demux modules with OSC	15540-MDXD-04A0	4-channel Band A	12.1(10)EV1
	15540-MDXD-04B0	4-channel Band B	12.1(10)EV1
	15540-MDXD-04C0	4-channel Band C	12.1(10)EV1
	15540-MDXD-04D0	4-channel Band D	12.1(10)EV1
	15540-MDXD-04E0	4-channel Band E	12.1(10)EV1
	15540-MDXD-04F0	4-channel Band F	12.1(10)EV1
	15540-MDXD-04G0	4-channel Band G	12.1(10)EV1
	15540-MDXD-04H0	4-channel Band H	12.1(10)EV1
	15540-MDXD-08A0	8-channel Band AB	12.1(10)EV1
	15540-MDXD-08B0	8-channel Band CD	12.1(10)EV1
	15540-MDXD-08C0	8-channel Band EF	12.1(10)EV1
	15540-MDXD-08D0	8-channel Band GH	12.1(10)EV1
	15540-MDXD-32A0	32-channel AH	12.1(10)EV1

Table 1 Cisco ONS 15540 ESPx Supported Hardware Modules and Minimum Software Requirements (Continued)

Component	Part Number	Description	Minimum Software Version Required
Line card motherboards	15540-LCMB-1100	Supports four transponders with protection or four extended range transponders with protection	12.1(10)EV1
	15540-LCMB-1200	Supports four transponders without protection or four extended range transponders without protection	12.1(10)EV1
	15540-LCMB-1400	Supports two 10-GE transponders with protection	12.1(10)EV2
	15540-LCMB-1401	Supports two 10-GE transponders without protection	12.1(10)EV2
MM transponder modules	15540-TSP1-01A3	Ch 1-2 —1310-nm MM 16 to 622 Mbps with SC	12.1(10)EV1
	15540-TSP1-03A3	Ch 3-4 —1310-nm MM 16 to 622 Mbps with SC	12.1(10)EV1
	15540-TSP1-05A3	Ch 5-6 —1310-nm MM 16 to 622 Mbps with SC	12.1(10)EV1
	15540-TSP1-07A3	Ch 7-8 — 310-nm MM 16 to 622 Mbps with SC	12.1(10)EV1
	15540-TSP1-09A3	Ch 9-10 — 1310-nm MM 16 to 622 Mbps with SC	12.1(10)EV1
	15540-TSP1-11A3	Ch 11-12 — 1310-nm MM 16 to 622 Mbps with SC	12.1(10)EV1
	15540-TSP1-13A3	Ch 13-14 — 1310-nm MM 16 to 622 Mbps with SC	12.1(10)EV1
	15540-TSP1-15A3	Ch 15-16 —1310-nm MM 16 to 622 Mbps with SC	12.1(10)EV1
	15540-TSP1-17A3	Ch 17-18 —1310-nm MM 16 to 622 Mbps with SC	12.1(10)EV1
	15540-TSP1-19A3	Ch 19-20 —1310nm MM 16 to 622 Mbps with SC	12.1(10)EV1
	15540-TSP1-21A3	Ch 21-22 —1310-nm MM 16 to 622 Mbps with SC	12.1(10)EV1
	15540-TSP1-23A3	Ch 23- 24—1310-nm MM 16 to 622 Mbps with SC	12.1(10)EV1
	15540-TSP1-25A3	Ch 25-26—1310-nm MM 16 to 622 Mbps with SC	12.1(10)EV1
	15540-TSP1-27A3	Ch 27-28—1310-nm MM 16 to 622 Mbps with SC	12.1(10)EV1
	15540-TSP1-29A3	Ch 29-30—1310-nm MM 16 to 622 Mbps with SC	12.1(10)EV1
15540-TSP1-31A3	Ch 31-32—1310-nm MM 16 to 622 Mbps with SC	12.1(10)EV1	

Table 1 Cisco ONS 15540 ESPx Supported Hardware Modules and Minimum Software Requirements (Continued)

Component	Part Number	Description	Minimum Software Version Required
SM transponder modules	15540-TSP1-01B3	Ch 1-2—1310-nm SM 16 Mbps to 2.5 Gbps with SC	12.1(10)EV1
	15540-TSP1-03B3	Ch 3-4—1310-nm SM 16 Mbps to 2.5 Gbps with SC	12.1(10)EV1
	15540-TSP1-05B3	Ch 5-6—1310-nm SM 16 Mbps to 2.5 Gbps with SC	12.1(10)EV1
	15540-TSP1-07B3	Ch 7-8—1310-nm SM 16 Mbps to 2.5 Gbps with SC	12.1(10)EV1
	15540-TSP1-09B3	Ch 9-10—1310-nm SM 16 Mbps to 2.5 Gbps with SC	12.1(10)EV1
	15540-TSP1-11B3	Ch 11-12—1310-nm SM 16 Mbps to 2.5 Gbps with SC	12.1(10)EV1
	15540-TSP1-13B3	Ch 13-14— 1310-nm SM 16 Mbps to 2.5 Gbps with SC	12.1(10)EV1
	15540-TSP1-15B3	Ch 15-16—1310-nm SM 16 Mbps to 2.5 Gbps with SC	12.1(10)EV1
	15540-TSP1-17B3	Ch 17-18—1310-nm SM 16 Mbps to 2.5 Gbps with SC	12.1(10)EV1
	15540-TSP1-19B3	Ch 19-20—1310nm SM 16 Mbps to 2.5 Gbps with SC	12.1(10)EV1
	15540-TSP1-21B3	Ch 21-22—1310-nm SM 16 Mbps to 2.5 Gbps with SC	12.1(10)EV1
	15540-TSP1-23B3	Ch 23- 24—1310-nm SM 16 Mbps to 2.5 Gbps with SC	12.1(10)EV1
	15540-TSP1-23B3	Ch 23- 24—1310-nm SM 16 Mbps to 2.5 Gbps with SC	12.1(10)EV1
	15540-TSP1-25B3	Ch 25-26—1310-nm SM 16 Mbps to 2.5 Gbps with SC	12.1(10)EV1
	15540-TSP1-27B3	Ch 27-28—1310-nm SM 16 Mbps to 2.5 Gbps with SC	12.1(10)EV1
	15540-TSP1-29B3	Ch 29-30 —1310-nm SM 16 Mbps to 2.5 Gbps with SC	12.1(10)EV1
15540-TSP1-31B3	Ch 31-32—1310-nm SM 16 Mbps to 2.5 Gbps with SC	12.1(10)EV1	
Type 2 extended range transponder modules with SFP optics	15540-TSP2-0100	Ch 1-2	12.1(10)EV1
	15540-TSP2-0300	Ch 3-4	12.1(10)EV1
	15540-TSP2-0500	Ch 5-6	12.1(10)EV1
	15540-TSP2-0700	Ch 7-8	12.1(10)EV1
	15540-TSP2-0900	Ch 9-10	12.1(10)EV1
	15540-TSP2-1100	Ch 11-12	12.1(10)EV1
	15540-TSP2-1300	Ch 13-14	12.1(10)EV1
	15540-TSP2-1500	Ch 15-16	12.1(10)EV1
	15540-TSP2-1700	Ch 17-18	12.1(10)EV1
	15540-TSP2-1900	Ch 19-20	12.1(10)EV1
	15540-TSP2-2100	Ch 21-22	12.1(10)EV1
	15540-TSP2-2300	Ch 23-24	12.1(10)EV1
	15540-TSP2-2500	Ch 25-26	12.1(10)EV1
	15540-TSP2-2700	Ch 27-28	12.1(10)EV1
	15540-TSP2-2900	Ch 29-30	12.1(10)EV1
15540-TSP2-3100	Ch 31-32	12.1(10)EV1	

Table 1 Cisco ONS 15540 ESPx Supported Hardware Modules and Minimum Software Requirements (Continued)

Component	Part Number	Description	Minimum Software Version Required
Single port 10-Gigabit Ethernet transponder modules	15540-10GE-03B301	10-GE 1310-nm SM Client with SC and ITU Laser Ch 1	12.1(10)EV2
	15540-10GE-03B302	10-GE 1310-nm SM Client with SC and ITU Laser Ch 2	12.1(10)EV2
	15540-10GE-03B303	10-GE 1310-nm SM Client with SC and ITU Laser Ch 3	12.1(10)EV2
	15540-10GE-03B304	10-GE 1310-nm SM Client with SC and ITU Laser Ch 4	12.1(10)EV2
	15540-10GE-03B305	10-GE 1310-nm SM Client with SC and ITU Laser Ch 5	12.1(10)EV2
	15540-10GE-03B306	10-GE 1310-nm SM Client with SC and ITU Laser Ch 6	12.1(10)EV2
	15540-10GE-03B307	10-GE 1310-nm SM Client with SC and ITU Laser Ch 7	12.1(10)EV2
	15540-10GE-03B308	10-GE 1310-nm SM Client with SC and ITU Laser Ch8	12.1(10)EV2
	15540-10GE-03B309	10-GE 1310-nm SM Client with SC and ITU Laser Ch 9	12.1(10)EV2
	15540-10GE-03B3010	10-GE 1310-nm SM Client with SC and ITU Laser Ch 10	12.1(10)EV2
	15540-10GE-03B3011	10-GE 1310-nm SM Client with SC and ITU Laser Ch 11	12.1(10)EV2
	15540-10GE-03B3012	10-GE 1310-nm SM Client with SC and ITU Laser Ch 12	12.1(10)EV2
	15540-10GE-03B3013	10-GE 1310-nm SM Client with SC and ITU Laser Ch 13	12.1(10)EV2
	15540-10GE-03B3014	10-GE 1310-nm SM Client with SC and ITU Laser Ch 14	12.1(10)EV2
	15540-10GE-03B3015	10-GE 1310-nm SM Client with SC and ITU Laser Ch 15	12.1(10)EV2
	15540-10GE-03B3016	10-GE 1310-nm SM Client with SC and ITU Laser Ch 16	12.1(10)EV2
	15540-10GE-03B3017	10-GE 1310-nm SM Client with SC and ITU Laser Ch 17	12.1(10)EV2
	15540-10GE-03B3018	10-GE 1310-nm SM Client with SC and ITU Laser Ch 18	12.1(10)EV2
	15540-10GE-03B3019	10-GE 1310-nm SM Client with SC and ITU Laser Ch 19	12.1(10)EV2
	15540-10GE-03B3020	10-GE 1310-nm SM Client with SC and ITU Laser Ch 20	12.1(10)EV2
	15540-10GE-03B3021	10-GE 1310-nm SM Client with SC and ITU Laser Ch 21	12.1(10)EV2
	15540-10GE-03B3022	10-GE 1310-nm SM Client with SC and ITU Laser Ch 22	12.1(10)EV2
	15540-10GE-03B3023	10-GE 1310-nm SM Client with SC and ITU Laser Ch 23	12.1(10)EV2
	15540-10GE-03B3024	10-GE 1310-nm SM Client with SC and ITU Laser Ch 24	12.1(10)EV2
	15540-10GE-03B3025	10-GE 1310-nm SM Client with SC and ITU Laser Ch 25	12.1(10)EV2
	15540-10GE-03B3026	10-GE 1310-nm SM Client with SC and ITU Laser Ch 26	12.1(10)EV2
	15540-10GE-03B3027	10-GE 1310-nm SM Client with SC and ITU Laser Ch 27	12.1(10)EV2
	15540-10GE-03B3028	10-GE 1310-nm SM Client with SC and ITU Laser Ch 28	12.1(10)EV2
	15540-10GE-03B3029	10-GE 1310-nm SM Client with SC and ITU Laser Ch 29	12.1(10)EV2
	15540-10GE-03B3030	10-GE 1310-nm SM Client with SC and ITU Laser Ch 30	12.1(10)EV2
	15540-10GE-03B3031	10-GE 1310-nm SM Client with SC and ITU Laser Ch 31	12.1(10)EV2
	15540-10GE-03B3032	10-GE 1310-nm SM Client with SC and ITU Laser Ch 32	12.1(10)EV2

Table 1 Cisco ONS 15540 ESPx Supported Hardware Modules and Minimum Software Requirements (Continued)

Component	Part Number	Description	Minimum Software Version Required
SFP optics for extended range transponder modules	15500-XVRA-01A2	ESCON and OC-3 1310-nm MM MT-RJ	12.1(10)EV1
	15500-XVRA-03B1	Gigabit Ethernet and Fibre Channel (1 Gbps) 1310-nm SM MTLC	12.1(10)EV1
	15500-XVRA-03B2	Fibre Channel (1 Gbps and 2 Gbps) 1310-nm SM MTLC	12.1(10)EV1
	15500-XVRA-02C1	Gigabit Ethernet and Fibre Channel (1 Gbps) 850-nm MM MTLC	12.1(10)EV1
	15500-XVRA-02C2	Fibre Channel (1 Gbps and 2 Gbps) 850-nm MM MTLC	12.1(10)EV1
	15500-XVRA-06B1	SONET OC-12 1310-nm SM MTLC	12.1(10)EV1
	15500-XVRA-07B1	SONET OC-48 1310-nm SM MTLC	12.1(10)EV1
Variable rate SFP optics	15500-XVRA-10A1	Low band (16 to 200 Mbps) variable rate, MM (1310 nm) with LC	12.1(12c)EV3
	15500-XVRA-10B1	Low band (16 to 200 Mbps) variable rate, SM (1310 nm) with LC	12.1(12c)EV3
	15500-XVRA-11A1	Mid band (200 to 622 Mbps) variable rate, MM (1310 nm) with LC	12.1(12c)EV3
	15500-XVRA-11B1	Mid band (200 to 1250 Mbps) variable rate, SM (1310 nm) with LC	12.1(12c)EV3
	15500-XVRA-12B1	High band (1.062 Gbps to 2.5 Gbps) variable rate, SM (1310 nm) with LC	12.1(12c)EV3
Protection switch module	15540-PSM-01	ONS 15540 protection switch module	12.1(12c)EV
Optical cross connect	15500-CCDK01	ONS 15500 cross connect drawer kit	12.1(10)EV1
	15500-CSDK01	ONS 15500 cable storage drawer kit	12.1(10)EV1
	15500-VC GK01	ONS 15500 vertical cable guide kit	12.1(10)EV1
	15500-CAB-MU-ADTR=	ONS 15540 MU-MU insertion adapter	12.1(10)EV1
	15500-CAB-TL01=	Cable installation and removal tool. SFP removal tool.	12.1(10)EV1
Optical cable kits	15500-CAB-KIT1	Cable Kit 1 - (order 1x for LCMB without splitter, order 2x for line card motherboard with splitter): 2x MTP-8MU, 2x MU adapter, 8x MU-MU	12.1(10)EV1
	15500-CAB-KIT2	Cable Kit 2 - 10G lower channels - (order 1x for every 10G line card motherboard with w/o splitter, order 2x for line card motherboard with w/ splitter): 1x MTP-8MU, 1x MTP-4MU, 2x MU adapter, 4x MU-MU	12.1(10)EV1
	15500-CAB-KIT3	Cable Kit 3 - 10G higher channels - (order 1x for every 10G line card motherboard with w/o splitter, order 2x for LCMB w/ splitter): 1x MTP-8MU, 1x MTP-4MU, 2x MU adapter, 4x MU-MU	12.1(10)EV1

Table 1 Cisco ONS 15540 ESPx Supported Hardware Modules and Minimum Software Requirements (Continued)

Component	Part Number	Description	Minimum Software Version Required
MTP cables	15500-CAB-MTP-01=	86" MTP to MTP cable - 2.5-Gbps line card motherboard	12.1(10)EV1
	15500-CAB-MTPMU-M	86" MTP to 8 MU optical cable - mux/demux to cross connect drawer - (Gray)	12.1(10)EV1
	15500-CAB-MTPMU-L	86" MTP to 8 MU optical cable - line card to cross connect drawer - (Green)	12.1(10)EV1
	15500-CAB-MTPMU-1	86" MTP to 4 MU optical cable-10G Ch 1/2 (Aqua)	12.1(10)EV1
	15500-CAB-MTPMU-2	86" MTP to 4 MU optical cable- 10G Ch 3/4 (Rose)	12.1(10)EV1
	15500-CAB-MTP-01,	86" MTP to MTP cable- 2.5G line card motherboard (Blue)	12.1(10)EV1
	15500-CAB-MTP-02	86" MTP to MTP cable - 10G line card motherboard-Ch. 1/2 (Aqua)	12.1(10)EV1
	15500-CAB-MTP-03	86" MTP to MTP cable - 10G line card motherboard-Ch. 3/4 (Rose)	12.1(10)EV1
	15500-CAB-MTP-04	86" MTP to 2x MTP cable - 10G line card motherboard Y-cable (Violet)	12.1(10)EV1
Optical trunk cables (simplex)	15500-CAB-MSC01=	1.0-m tuned low loss MU to SC SM patch cable	12.1(10)EV1
	15500-CAB-MSC02=	3.0-m tuned low loss MU to SC SM patch cable	12.1(10)EV1
	15500-CAB-MST03=	1.0-m Tuned low loss MU to ST SM patch cable	12.1(10)EV1
	15500-CAB-MST04=	3.0-m Tuned low loss MU to ST SM patch cable	12.1(10)EV1
Optical OADM and intra chassis cables (simplex)	15500-CAB-MMU-01=	0.25-m (10") tuned low loss MU to MU SM OADM patch cable	12.1(10)EV1
	15500-CAB-MMU-02=	0.35-m (14") tuned low loss MU to MU SM OADM patch cable	12.1(10)EV1
	15500-CAB-MMU-03=	0.45-m (17") tuned low loss MU to MU SM OADM patch cable	12.1(10)EV1
	15500-CAB-MMU-04=	0.5-m (20") tuned low loss MU to MU SM OADM patch cable	12.1(10)EV1
	15500-CAB-MMU-05=	1.0-m (40") tuned low loss MU to MU SM OADM patch cable	12.1(10)EV1
	15500-CAB-MMU-09=	1.16-m (46") tuned low loss MU to MU SM OADM patch cable	12.1(10)EV1
	15500-CAB-MMU-06=	1.5-m (60") tuned low loss MU to MU SM OADM patch cable	12.1(10)EV1
	15500-CAB-MMU-07=	2.0-m (79") tuned low loss MU to MU SM OADM patch cable	12.1(10)EV1
	15500-CAB-MMU-08=	2.5-m (98") tuned low loss MU to MU SM OADM patch cable	12.1(10)EV1

Table 1 Cisco ONS 15540 ESPx Supported Hardware Modules and Minimum Software Requirements (Continued)

Component	Part Number	Description	Minimum Software Version Required
Optical client cables (simplex)	15500-CAB-SC11=	1.0-m SC to SC 62.5/125m MM cable	12.1(10)EV1
	15500-CAB-SC19=	1.0-m SC to SC 50/125m MM cable	12.1(10)EV1
	15500-CAB-SC12=	1.0-m SC to SC SM cable	12.1(10)EV1
	15500-CAB-SC13=	3.0-m SC to SC 62.5/125m MM cable	12.1(10)EV1
	15500-CAB-SC20=	3.0-m SC to SC 50/125m MM cable	12.1(10)EV1
	15500-CAB-SC14=	3.0-m SC to SC SM cable	12.1(10)EV1
	15500-CAB-ST15=	1.0-m SC to ST 62.5/125m MM cable	12.1(10)EV1
	15500-CAB-ST21=	1.0-m SC to ST 50/125m MM cable	12.1(10)EV1
	15500-CAB-ST16=	1.0-m SC to ST SM cable	12.1(10)EV1
	15500-CAB-ST17=	3.0-m SC to ST 62.5/125m MM cable	12.1(10)EV1
	15500-CAB-ST22=	3.0-m SC to ST 50/125m MM cable	12.1(10)EV1
Optical y-cables	15500-CAB-YMM-SC=	50/125m multimode y cable with SC for channel protection	12.1(10)EV1
	15500-CAB-YMM2-SC=	62.5/125m multimode y cable with SC for channel protection	12.1(10)EV1
	15500-CAB-YSM-SC=	Single mode y cable with SC for channel protection	12.1(10)EV1
	15500-CAB-YMM-SC=	50/125m multimode y cable with SC for channel protection	12.1(10)EV1

Determining the Software Version



Note

We strongly recommend that you use the latest available software release for all Cisco ONS 15540 ESPx hardware.

To determine the version of Cisco IOS software currently running on a Cisco ONS 15540 ESPx system, log in to the system and enter the **show version EXEC** command.

Upgrading the System Image

To ensure proper system functioning, follow the system image upgrading procedure described in the *Cisco ONS 15540 ESPx Software Upgrade Guide*.



Note

Always set the configuration register to 0x2102 when upgrading the system image using the **config-reg 0x2102** command in configuration mode.

**Caution**

Improper system image upgrades can affect system functioning and redundancy. Always follow the recommended upgrade procedures.

Feature Set Table

The Cisco IOS Release software is packaged in feature sets (also called software images) depending on the platform. Each feature set contains a specific set of Cisco IOS software features. [Table 2](#) lists the Cisco IOS software feature sets available for the Cisco ONS 15540 ESPx.

Table 2 Feature Sets Supported by the Cisco ONS 15540 ESPx

Feature Set	Introduced in this Release
Gigabit Ethernet	12.1(10)EV
Fast Ethernet	12.1(10)EV
Ethernet	12.1(10)EV
ATM OC-3/STM-1, OC-12/STM-4, and OC-48/STM-16	12.1(10)EV
SONET ¹ /SDH ²	12.1(10)EV
POS ³	12.1(10)EV
Fibre Channel (1 Gbps)	12.1(10)EV
Fibre Channel (2 Gbps)	12.1(10)EV
FDDI ⁴	12.1(10)EV
ESCON ⁵ SM (200 Mbps)	12.1(10)EV
FICON ⁶ (800 Mbps)	12.1(10)EV
FICON (1 Gbps)	12.2(18)SV
Token Ring	12.1(10)EV
SNMP	12.1(10)EV
CiscoView	12.1(10)EV
Cisco Transport Manager	12.1(10)EV
CDP ⁷	12.1(10)EV
IP packets	12.1(10)EV
OSCP ⁸	12.1(10)EV
APS ⁹ protocol packets	12.1(10)EV
Point-to-point	12.1(10)EV
Hubbed ring	12.1(10)EV
Meshed ring	12.1(10)EV
IBM GDPS ¹⁰ ETR/CLO ¹¹	12.1(10)EV1
IBM GDPS ¹⁰ coupling link	12.1(10)EV1
Unidirectional path switching	12.1(10)EV

Table 2 Feature Sets Supported by the Cisco ONS 15540 ESPx (Continued)

Feature Set	Introduced in this Release
Bidirectional path switching	12.1(10)EV
CDL over 10 GE	12.1(10)EV2
2-Gbps Fibre Channel protocol monitoring on transparent transponder	12.2(18)SV
2-Gbps FICON protocol monitoring	12.2(18)SV
Functional image version diagnostics	12.2(18)SV

1. SONET = Synchronous Optical Networking
2. SDH = Synchronous Digital Hierarchy
3. POS = Packet over SONET
4. FDDI = Fiber Distributed Data Interface
5. ESCON = Enterprise Systems Connection
6. FICON = Fiber Connection
7. CDP = Cisco Discovery Protocol
8. OSCP = Optical Supervisory Channel Protocol
9. APS = Automatic Protection Switching
10. GDPS = Geographically Dispersed Parallel Sysplex
11. ETR/CLO = external timer reference/control link oscillator

New Features in Release 12.2(18)SV

The following new software features are available for the Cisco ONS 15540 ESPx in Cisco IOS Release 12.2(18)SV:

- 2-Gbps Fibre Channel protocol monitoring



Note 2-Gbps Fibre Channel protocol monitoring requires transponder functional image release 1.A3.

- 2-Gbps FICON protocol monitoring
- Data file with upgrade information for the ROMMON and functional images
- **show upgrade-info functional-image** command

Caveats

This section describes open and resolved severity 1 and 2 caveats and select severity 3 caveats: The “Open Caveats” section lists open caveats that apply to the current release and may apply to previous releases. The “Resolved Caveats” sections list caveats resolved in a particular release, but open in previous releases.

Open Caveats in Release 12.2(18)SV

- CSCec08603
Symptom: In a configuration with 10-GE transponder modules, switchover eventually fails when continuous back and forth switchovers are performed from working to protection.
Workaround: None.
- CSCec18408
Symptom: A y-cable APS bidirectional switchover caused by a trunk Rx failure takes as long as two seconds in a configuration with 10-GE transponder modules.
Workaround: None.
- CSCec28182
Symptom: Tracebacks related to CPU hog issues are seen when reprogramming the 2.5-Gbps transponder module functional image.
Workaround: None.
- CSCec31146
Symptom: When monitoring is disabled, Loss of Light on the local transparent interface results in Loss of Sync on the far side wave interface.
Workaround: Enable monitoring on the transparent interface.

Resolved Caveats for Release 12.2(18)SV

- CSCdu53656
A Cisco device running IOS and enabled for the Border Gateway Protocol (BGP) is vulnerable to a Denial of Service (DOS) attack from a malformed BGP packet. The BGP protocol is not enabled by default, and must be configured in order to accept traffic from an explicitly defined peer. Unless the malicious traffic appears to be sourced from a configured, trusted peer, it would be difficult to inject a malformed packet. BGP MD5 is a valid workaround for this problem.
Cisco has made free software available to address this problem. For more details, please refer to this advisory, available at <http://www.cisco.com/warp/public/707/cisco-sa-20040616-bgp.shtml>.
- CSCea28131
A Cisco device running IOS and enabled for the Border Gateway Protocol (BGP) is vulnerable to a Denial of Service (DOS) attack from a malformed BGP packet. The BGP protocol is not enabled by default, and must be configured in order to accept traffic from an explicitly defined peer. Unless the malicious traffic appears to be sourced from a configured, trusted peer, it would be difficult to inject a malformed packet. BGP MD5 is a valid workaround for this problem.
Cisco has made free software available to address this problem. For more details, please refer to this advisory, available at <http://www.cisco.com/warp/public/707/cisco-sa-20040616-bgp.shtml>.
- CSCeb61427
Symptom: The system crashes when the user exits from the console after the active processor card has been removed and inserted online and is switched back to being the active processor card.
Workaround: None.
- CSCeb72528

Symptom: Client Tx fault alarm is asserted when an SFP optics is inserted or upon a y-cable switchover.

Workaround: Upgrade to Cisco IOS Release 12.1(12c)EV3 and transponder functional image version 1.A2 or higher.

- CSCec05746

Symptom: In a point-to-point network topology setup where bidirectional PSM trunk fiber protection APS is configured, and the in-band message channel is configured for dcc and the controller type of the OADM filter is 0x1104 (4-channel OADM without OSC), APS is unable to track a valid ethernetDcc interface. Therefore the group cannot be associated.

Workaround: Do not configure in-band message channel as dcc for PSM APS if the corresponding OADM module does not have OSC ports (controller type 0x1104).

- CSCec22377

Symptom: Continuous optical performance monitoring alarms cause memory leaks that lead to bus error exceptions and an unexpected reload.

Workaround: None.

- CSCec31512

Symptom: The standby processor card crashes when bus error exceptions are reported at ipc_process_timeout, when doing a send "brk" from a Telnet session, to the active processor card.

Workaround: None.

Limitations and Restrictions

This section provides limitations and restrictions for Cisco ONS 15540 ESPx hardware and software.

Transponder Modules

This section contains limitations and restrictions that apply to transponder modules.

- When you insert the standby transponder module in a y-cable protected configuration, remove the cable from the transponder module before inserting the transponder module into the shelf. Failure to remove the cable might result in errors that can affect the performance of the active signal received by the client equipment.
- CRC errors occur with 2-Gbps Fibre Channel on single-mode transponder modules when high input power levels are received from the client laser sources.

Data errors or link-down conditions for 2-Gbps Fibre Channel might occur on single-mode transponder modules when used with certain client laser sources. Transmitters in some client GBIC and SFP transceiver units might send large overshoots in optical power with signal bit transitions, causing momentary overload conditions on the transponder module client side receiver. The average transmitted power level from the GBIC does not violate the overload specification of the transponder module client side receiver, so a power meter does not detect the overload.

The workaround is to attenuate the signal from the client equipment to a recommended level of -12 dBm when transmitting 2-Gbps Fibre Channel services.

- Error-free transmission of some D1 video signals (defined by the SMPTE 259M standard) and test patterns (such as Matrix SDI) cannot be guaranteed by the Cisco 15500 Series because of the pathological pattern in D1 video. This well-known limitation is usually overcome by the D1 video equipment vendor, who uses a proprietary, second level of scrambling. No standards exist at this time for the second level of scrambling
- If both processor cards are removed, traffic through the system is affected as follows:
 - For Type 2 extended range transponder modules, traffic is shut down.
 - For 10-GE transponder modules, traffic is shut down.
 - Type 1 SM transponder modules and MM transponder modules do not operate reliably. The traffic might be affected.
 - In the shutdown state, the Status LED on the line card motherboard turns orange.



Note Traffic on pass through optical channels (which passively pass through the mux/demux modules) are not affected by the removal of the processor cards.

Related Documentation

Refer to the following documents for more information about the Cisco ONS 15540 ESPx:

- [Regulatory Compliance and Safety Information for the Cisco ONS 15500 Series](#)
- [Cisco ONS 15540 ESPx Planning Guide](#)
- [Cisco ONS 15540 ESPx Hardware Installation Guide](#)
- [Cisco ONS 15540 ESPx Optical Transport Turn-Up and Test Guide](#)
- [Cisco ONS 15540 ESPx Cleaning Procedures for Fiber Optic Connections](#)
- [Cisco ONS 15540 ESPx Configuration Guide](#)
- [Cisco ONS 15540 ESPx Command Reference](#)
- [Cisco ONS 15540 ESPx System Alarms and Error Messages](#)
- [Cisco ONS 15540 ESPx Troubleshooting Guide](#)
- [Network Management for the Cisco ONS 15540 ESPx](#)
- [Cisco ONS 15540 ESPx TL1 Commands](#)
- [MIB Quick Reference for the Cisco ONS 15500 Series](#)
- [Cisco ONS 15540 ESPx Software Upgrade Guide](#)

Obtaining Documentation

Cisco provides several ways to obtain documentation, technical assistance, and other technical resources. These sections explain how to obtain technical information from Cisco Systems.

Cisco.com

You can access the most current Cisco documentation on the World Wide Web at this URL:

<http://www.cisco.com/univercd/home/home.htm>

You can access the Cisco website at this URL:

<http://www.cisco.com>

International Cisco websites can be accessed from this URL:

http://www.cisco.com/public/countries_languages.shtml

Documentation CD-ROM

Cisco documentation and additional literature are available in a Cisco Documentation CD-ROM package, which may have shipped with your product. The Documentation CD-ROM is updated regularly and may be more current than printed documentation. The CD-ROM package is available as a single unit or through an annual or quarterly subscription.

Registered Cisco.com users can order a single Documentation CD-ROM (product number DOC-CONDOCCD=) through the Cisco Ordering tool:

http://www.cisco.com/en/US/partner/ordering/ordering_place_order_ordering_tool_launch.html

All users can order annual or quarterly subscriptions through the online Subscription Store:

<http://www.cisco.com/go/subscription>

Click Subscriptions & Promotional Materials in the left navigation bar.

Ordering Documentation

You can find instructions for ordering documentation at this URL:

http://www.cisco.com/univercd/cc/td/doc/es_inpck/pdi.htm

You can order Cisco documentation in these ways:

- Registered Cisco.com users (Cisco direct customers) can order Cisco product documentation from the Networking Products MarketPlace:

<http://www.cisco.com/en/US/partner/ordering/index.shtml>

- Nonregistered Cisco.com users can order documentation through a local account representative by calling Cisco Systems Corporate Headquarters (California, USA) at 408 526-7208 or, elsewhere in North America, by calling 800 553-NETS (6387).

Documentation Feedback

You can submit e-mail comments about technical documentation to bug-doc@cisco.com.

You can submit comments by using the response card (if present) behind the front cover of your document or by writing to the following address:

Cisco Systems
Attn: Customer Document Ordering
170 West Tasman Drive
San Jose, CA 95134-9883

We appreciate your comments.

Obtaining Technical Assistance

For all customers, partners, resellers, and distributors who hold valid Cisco service contracts, the Cisco Technical Assistance Center (TAC) provides 24-hour-a-day, award-winning technical support services, online and over the phone. Cisco.com features the Cisco TAC website as an online starting point for technical assistance. If you do not hold a valid Cisco service contract, please contact your reseller.

Cisco TAC Website

The Cisco TAC website (<http://www.cisco.com/tac>) provides online documents and tools for troubleshooting and resolving technical issues with Cisco products and technologies. The Cisco TAC website is available 24 hours a day, 365 days a year.

Accessing all the tools on the Cisco TAC website requires a Cisco.com user ID and password. If you have a valid service contract but do not have a login ID or password, register at this URL:

<http://tools.cisco.com/RPF/register/register.do>

Opening a TAC Case

Using the online TAC Case Open Tool (<http://www.cisco.com/tac/caseopen>) is the fastest way to open P3 and P4 cases. (P3 and P4 cases are those in which your network is minimally impaired or for which you require product information.) After you describe your situation, the TAC Case Open Tool automatically recommends resources for an immediate solution. If your issue is not resolved using the recommended resources, your case will be assigned to a Cisco TAC engineer.

For P1 or P2 cases (P1 and P2 cases are those in which your production network is down or severely degraded) or if you do not have Internet access, contact Cisco TAC by telephone. Cisco TAC engineers are assigned immediately to P1 and P2 cases to help keep your business operations running smoothly.

To open a case by telephone, use one of the following numbers:

Asia-Pacific: +61 2 8446 7411 (Australia: 1 800 805 227)

EMEA: +32 2 704 55 55

USA: 1 800 553-2447

For a complete listing of Cisco TAC contacts, go to this URL:

<http://www.cisco.com/warp/public/687/Directory/DirTAC.shtml>

TAC Case Priority Definitions

To ensure that all cases are reported in a standard format, Cisco has established case priority definitions.

Priority 1 (P1)—Your network is “down” or there is a critical impact to your business operations. You and Cisco will commit all necessary resources around the clock to resolve the situation.

Priority 2 (P2)—Operation of an existing network is severely degraded, or significant aspects of your business operation are negatively affected by inadequate performance of Cisco products. You and Cisco will commit full-time resources during normal business hours to resolve the situation.

Priority 3 (P3)—Operational performance of your network is impaired, but most business operations remain functional. You and Cisco will commit resources during normal business hours to restore service to satisfactory levels.

Priority 4 (P4)—You require information or assistance with Cisco product capabilities, installation, or configuration. There is little or no effect on your business operations.

Obtaining Additional Publications and Information

Information about Cisco products, technologies, and network solutions is available from various online and printed sources.

- The Cisco Product Catalog describes the networking products offered by Cisco Systems, as well as ordering and customer support services. Access the Cisco Product Catalog at this URL:
http://www.cisco.com/en/US/products/products_catalog_links_launch.html
- Cisco Press publishes a wide range of general networking, training and certification titles. Both new and experienced users will benefit from these publications. For current Cisco Press titles and other information, go to Cisco Press online at this URL:
<http://www.ciscopress.com>
- Packet magazine is the Cisco quarterly publication that provides the latest networking trends, technology breakthroughs, and Cisco products and solutions to help industry professionals get the most from their networking investment. Included are networking deployment and troubleshooting tips, configuration examples, customer case studies, tutorials and training, certification information, and links to numerous in-depth online resources. You can access Packet magazine at this URL:
<http://www.cisco.com/packet>
- iQ Magazine is the Cisco bimonthly publication that delivers the latest information about Internet business strategies for executives. You can access iQ Magazine at this URL:
<http://www.cisco.com/go/iqmagazine>
- Internet Protocol Journal is a quarterly journal published by Cisco Systems for engineering professionals involved in designing, developing, and operating public and private internets and intranets. You can access the Internet Protocol Journal at this URL:
http://www.cisco.com/en/US/about/ac123/ac147/about_cisco_the_internet_protocol_journal.html
- Training—Cisco offers world-class networking training. Current offerings in network training are listed at this URL:
<http://www.cisco.com/en/US/learning/index.html>

This document is to be used in conjunction with the documents listed in the “[Related Documentation](#)” section.

CCIP, CCSP, the Cisco Arrow logo, the Cisco *Powered* Network mark, Cisco Unity, Follow Me Browsing, FormShare, and StackWise are trademarks of Cisco Systems, Inc.; Changing the Way We Work, Live, Play, and Learn, and iQuick Study are service marks of Cisco Systems, Inc.; and Aironet, ASIST, BPX, Catalyst, CCDA, CCDP, CCIE, CCNA, CCNP, Cisco, the Cisco Certified Internetwork Expert logo, Cisco IOS, the Cisco IOS logo, Cisco Press, Cisco Systems, Cisco Systems Capital, the Cisco Systems logo, Empowering the Internet Generation, Enterprise/Solver, EtherChannel, EtherSwitch, Fast Step, GigaStack, Internet Quotient, IOS, IP/TV, iQ Expertise, the iQ logo, iQ Net Readiness Scorecard, LightStream, MGX, MICA, the Networkers logo, Networking Academy, Network Registrar, *Packet*, PIX, Post-Routing, Pre-Routing, RateMUX, Registrar, ScriptShare, SlideCast, SMARTnet, StrataView Plus, Stratm, SwitchProbe, TeleRouter, The Fastest Way to Increase Your Internet Quotient, TransPath, and VCO are registered trademarks of Cisco Systems, Inc. and/or its affiliates in the U.S. and certain other countries.

All other trademarks mentioned in this document or Web site are the property of their respective owners. The use of the word partner does not imply a partnership relationship between Cisco and any other company. (0304R)

Copyright © 2003 Cisco Systems, Inc. All rights reserved.